



Replacement parts are stocked for motors up to 200 frame

**To Order Spare Parts for the FM:P Range:**

**FIRST THREE DIGITS:**

Motor material and efficiency

Code	Range	Material
170	Standard Efficiency	Aluminium
171	Standard Efficiency	Cast Iron
172	Premium Efficiency	Aluminium
173	Premium Efficiency	Cast Iron

**FOURTH DIGIT:**

Frame size

Code	Frame
A	56
B	63
C	71
D	80
E	90
F	100
G	112
H	132
J	160
K	180
L	200
M	225
N	250
P	280
R	315
S	355
T	400
U	450
V	500
W	560

**FIFTH DIGIT:**

When ordering spare parts always use 9 as the fifth digit.

**SIXTH, SEVENTH & EIGHTH DIGIT:**

Please select relevant item number from the spare parts list above.



## Fenner FM:P Bearings

Frame Size	Poles	Driving End		Non Driving End		
		Ball Bearing	NU Bearing	Ball Bearing	Regreasable Bearings	V1 Mounting
80	2 - 10	<b>6204 2RZ</b>	–	<b>6204 2RZ</b>	–	6204 2RZ
56	2 - 4	<b>6201 2RZ</b>	–	<b>6201 2RZ</b>	–	6201 2RZ
63	2 - 4	<b>6201 2RZ</b>	–	<b>6201 2RZ</b>	–	6201 2RZ
71	2 - 6	<b>6202 2RZ</b>	–	<b>6202 2RZ</b>	–	6202 2RZ
80	2 - 8	<b>6204 2RZ</b>	–	<b>6204 2RZ</b>	–	6204 2RZ
90	2 - 8	<b>6205 2RZ</b>	–	<b>6205 2RZ</b>	–	6205 2RZ
100	2 - 8	<b>6206 2RZ</b>	–	<b>6206 2RZ</b>	–	6206 2RZ
112	2 - 8	<b>6206 2RZ</b>	–	<b>6206 2RZ</b>	–	6206 2RZ
132	2 - 8	<b>6208 2RZ</b>	–	<b>6208 2RZ</b>	–	6208 2RZ
160	2 - 12	6309 ZZ C3	<b>NU 309</b>	6309 ZZ C3	<b>6309 C3</b>	6309 ZZ C3
180	2 - 12	6311 ZZ C3	<b>NU 311</b>	6311 ZZ C3	<b>6311 C3</b>	6311 ZZ C3
200	2 - 12	6312 ZZ C3	<b>NU 312</b>	6312 ZZ C3	<b>6312 C3</b>	6312 ZZ C3
225	2 - 12	6313 ZZ C3	<b>NU 313</b>	6313 ZZ C3	<b>6313 C3</b>	6313 ZZ C3
250	2 - 12	6314 ZZ C3	<b>NU 314</b>	6314 ZZ C3	<b>6314 C3</b>	6314 ZZ C3
280	2	–	<b>NU 314</b>	–	<b>6314 C3</b>	6314 C3-EQ*
280	4 - 12	–	<b>NU 317</b>	–	<b>6317 C3</b>	6317 C3-EQ*
315	2	–	<b>NU 317</b>	–	<b>6317 C3</b>	6317 C3-EQ*
315	4 - 12	–	<b>NU 319</b>	–	<b>6319 C3</b>	6319 C3-EQ*
355	2	–	<b>NU 317</b>	–	<b>6317 C3</b>	7317 B
355	4 - 12	–	<b>NU 322</b>	–	<b>6320 C3</b>	7320 B
400	2	–	<b>NU 317</b>	–	<b>6317 C3</b>	7317 B
400	4 - 12	–	<b>NU 326</b>	–	<b>6326 C3</b>	7326 B
450	2	–	<b>NU 319</b>	–	<b>6319 C3</b>	7319 B
450	4 - 12	–	<b>NU 328</b>	–	<b>6328 C3</b>	7328 B
500	4 - 12	–	<b>NU 330</b>	–	<b>6330 C3</b>	7330 B
560	4 - 12	–	<b>NU 334</b>	–	<b>6330 C3</b>	7330 B

\*EQ = SKF Explorer Quality  
 Bold type indicates standard bearings.